

**AMENDMENTS TO THE CLAIMS**

*This listing of claims will replace all prior versions and listings of claims in this application.*

**LISTING OF CLAIMS:**

1. (Canceled)
2. (Canceled)
3. (Canceled)
4. (Currently Amended) ~~The device according to Claim 3, wherein~~ Device for protecting a bearing of an electrical machine against damaging passage of current, wherein the electrical machine comprises a stator and a rotor pivotally mounted relative to the stator by the bearing, the device comprising:  
a compensation circuit for producing a compensation current which compensates for a parasitic current arising during operation of the electrical machine and passing through the bearing, the compensation current has a corresponding magnitude as the parasitic current but opposite in phase to the parasitic current;  
a coupling element for direct or indirect coupling of the compensation current into the bearing;  
the compensation circuit comprising an artificial star point which prepares a star point voltage at which phase voltages for operation of the electrical machine are found, the artificial star point is formed by three identical impedances; and

the compensation circuit also ~~comprises~~ comprising a polarity reversal transformer having a primary side to which the star point voltage is supplied at least in part and a secondary side which produces a voltage opposite in phase to the star point voltage.

5. (Original) The device according to Claim 4, wherein the compensation circuit also comprises an amplitude matching stage connected between the artificial star point and the polarity reversal transformer, the amplitude matching stage applying an adjustable fraction of the star point voltage to the polarity reversal transformer.

6. (Original) The device according to Claim 5, wherein the polarity reversal transformer has several winding taps on the secondary side.

7. (Original) The device according to Claim 6, wherein the polarity reversal transformer is connected on the secondary side to an input of a frequency response matching stage which equalizes a frequency response of the compensation current to the parasitic current.

8. (Original) The device according to Claim 7, wherein an output of the frequency response matching stage is connected to the coupling element.

9. (Original) The device according to Claim 8, wherein the coupling element is arranged such that coupling of the compensation current takes place into a rotor shaft of the rotor by which the rotor in the bearing is pivotally mounted.

10. (Original) The device according to Claim 9, wherein the coupling element is a capacitor.

11. (Currently Amended) ~~The device according to Claim 2, wherein~~ Device for protecting a bearing of an electrical machine against damaging passage of current, wherein the electrical machine comprises a stator and a rotor pivotally mounted relative to the stator by the bearing, the device comprising:

a compensation circuit for producing a compensation current which compensates for a parasitic current arising during operation of the electrical machine and passing through the bearing, the compensation current has a corresponding magnitude as the parasitic current but opposite in phase to the parasitic current;

a coupling element for direct or indirect coupling of the compensation current into the bearing;

the compensation circuit comprising an artificial star point which prepares a star point voltage at which phase voltages for operation of the electrical machine are found; and

the compensation circuit also comprises comprising a polarity reversal transformer having a primary side to which the star point voltage is supplied at least in part and a secondary side which produces a voltage opposite in phase to the star point voltage.

12. (Original) The device according to Claim 11, wherein the compensation circuit also comprises an amplitude matching stage connected between the artificial star point and the polarity reversal transformer, the amplitude matching stage applying an adjustable fraction of the star point voltage to the polarity reversal transformer.

13. (Original) The device according to Claim 11, wherein the polarity reversal transformer has several winding taps on the secondary side.

14. (Original) The device according to Claim 11, wherein the polarity reversal transformer is connected on the secondary side to an input of a frequency response matching stage which equalizes a frequency response of the compensation current to the parasitic current.

15. (Original) The device according to Claim 14, wherein an output of the frequency response matching stage is connected to a coupling element.

16. (Original) The device according to Claim 15, wherein the coupling element is arranged such that coupling of the compensation current takes place into a rotor shaft of the rotor by which the rotor in the bearing is pivotally mounted.

17. (Original) The device according to Claim 15, wherein the coupling element is a capacitor.

18. (Canceled)

19. (Canceled)

20. (Currently Amended) ~~The device according to Claim 19, wherein~~  
Device for protecting a bearing, which supports a rotor of an electrical machine,  
against passage of parasitic current arising from operation of the electrical machine,  
the device comprising:  
means for producing a compensation current corresponding in magnitude to  
the parasitic current but opposite in phase to the parasitic current;  
coupling means for coupling the compensation current into the rotor;  
the means for producing compensation current comprising an artificial star  
point which prepares a star point voltage at which phase voltages for operation of the  
electrical machine exist; and  
the means for producing compensation current also ~~comprises~~ comprising a  
polarity reversal transformer having one side to which the star point voltage is at  
least partly supplied and a second side which produces a voltage opposite in phase  
to the star point voltage.

21. (Previously Presented) The device according to Claim 20, wherein the  
means for producing compensation current also comprises an amplitude matching  
stage connected between the artificial star point and the polarity reversal

transformer, the amplitude matching stage applying an adjustable fraction of the star point voltage to the polarity reversal transformer.

22. (Currently Amended) The device according to Claim ~~48~~ 20, wherein the coupling means couples the compensation current to the bearing element either directly or indirectly.